





5) Choose the device you need to upgrade and click the Upgrade button.



6) Select the firmware file obtained in 2 (For example WH2600\_v2.2.7.bin) and click Upgrade Firmware



- 7) The progress bar will fill from left to right – do not use your computer when the firmware is being installed.

Upgrade Firmware

FileName:

Do not perform any keyboard or mouse commands while the firmware is upgrading!

Upgrade info  
 Device Name:DSM1  
 Device IP:192.168.1.64  
 Device Mac:00-0E-C6-20-09-87

TFTP server @ 192.168.1.83 is running on UDP port 69 successfully.  
 Received a Read request from 192.168.1.64 on port 1026 (file: C:\Users\ivor\Download

IP Address	MAC Address

- 8) Once complete you will get confirmation and your receiver will then reboot.

Upgrade Firmware

FileName:


Upgrade Complete!

TFTP server @ 192.168.1.83 is running on UDP port 69 successfully.  
 Received a Read request from 192.168.1.64 on port 1026 (file: C:\Users\ivor\Download  
 Read session is completed successfully.  
 TFTP server stoped.


IP Address	MAC Address

If the upgrade fails, please follow the below steps:


- 1) Follow steps 1 to 4 from the instructions above. A device that failed to upgrade will not show on the device list. For example: if the receiver with MAC address 00-0E-C6-00-00-5A failed to upgrade - it will not show on the below list:




- 2) If the device doesn't show on the list, user to click upgrade button directly without choosing a device.



- 3) Select the firmware file obtained in 1 (For example WH2600\_v2.2.7.bin) and click Upgrade Firmware



- 4) The software will then scan your network for WeatherSleuth receivers and update them as above.



Upgrade Firmware

FileName:

Upgrade info  
 Device Name:DSM1  
 Device IP:10.10.10.115  
 Device Mac:00-0E-C6-00-00-5A

TFTP server @ 10.10.10.103 is running on UDP port 69 successfully.  
 Received a Read request from 10.10.10.115 on port 1026 (file: D:\Work\_item\WH2600  
 Read session is completed successfully.  
 TFTP server stoped.

IP Address	MAC Address



- 5) Click Choose File to Select the firmware file obtained in 2 (For example WH2600\_v2.2.7.bin) and click Update
- 6) The update will now proceed in the same way as the PC version.